



HX 6000 TB UK C5

PORTABLE POWER

GENERATING SET Range INTENS

PRODUCT ADVANTAGES

- Solid and high-performance equipment
- Generating set guaranteed 3 years
- HONDA Professional Engine

STAGE V (2016/1628 EU) : This product is compliant with regulation for implementing requirements relating to gaseous and pollutant emission limits in Europe

Range INTENS

Equipment that is robust, long-lasting and simple to use for repetitive operations in difficult conditions.



This product meets the Qualigen charter, which aims to ensure a high level of quality and guarantee the safety of users. Qualigen: commitment to safety and quality.

HX 6000 TB UK C5

GENERAL SPECIFICATIONS

Range	INTENS
Frequency (Hz)	50 Hz
Max power (kW) *	5.60
Nominal voltage (V)	230
Number of Phase	Single phase
Fuel	Petrol
Tank (L)	6.10
75% cons. (l/h) *	2.50
75% Autonomy (h) *	2.40
Sound power level guaranteed LwA dB(A)	97
Acoustic pressure level @1m in dB(A)	83
Acoustic pressure level @7m in dB(A)	69

ENGINE SPECIFICATIONS

Engine brand	HONDA
Engine type	GX390_C5
Engine Type	O.H.V.
Start	Starter
Oil shutdown	Oui
Displacement (cm ³)	389
Oil system capacity including filters (l)	1.10

ALTERNATOR SPECIFICATIONS

Technology	Brushless
AVR Regulation	No
Indication of protection	IP 23
Insulation class	H

PLUGS AND PANEL DESCRIPTIVE

1 115V 16A socket - circuit breaker + 1 115V 32A socket - circuit breaker + 2 230V 16A sockets - circuit breaker

DIMENSIONS AND WEIGHT

Length (cm)	77
Width (cm)	57
Height (cm)	59
Dry Weight (kg)	80

PACKAGING

Packaging type	Box
Length (cm)	78.50
Width (cm)	58
Height (cm)	59.50
Weight (kg)	82.50
Pallet type	120/80
Number of box by pallet	6
Pallet height (cm)	192
weight of the packaged Pallet (kg)	505

KOHLER®

SDMO®

HX 6000 TB UK C5

ACCESSORIES SUPPLIED



Funnel



User and maintenance manual

OPTIONS



R05M - Manual source inverter for connecting a single-phase generator to a house

Manual source inverter for connecting a single-phase generator to a house



RKB2 - Trolley kit for HX 4000 - 6000 – 7500T / HXC 4000 - 6000 – 7500T / TECHNIC 10000 -15000 / VX 200/4 -220-7,5 / WELDARC 300 / TRASH ; Puncture-proof wheels Ø 290 mm

Trolley kit for HX 4000 - 6000 – 7500T / HXC 4000 - 6000 – 7500T / TECHNIC 10000 -15000 / VX 200/4 -220-7,5 / WELDARC 300 / TRASH ; Puncture-proof wheels Ø 290 mm



R19 - Maintenance kit for HX 6000 - 7500 T / VX 200/4 including oil, spark plug and air filter

Maintenance kit for HX 6000 - 7500 T / VX 200/4 including oil, spark plug and air filter



16A blue 230V male plug - Sold per 1 or 10

16A blue 230V male plug - Sold per 1 or 10



16A yellow 115V male plug - Sold per 1 or 10

16A yellow 115V male plug - Sold per 1 or 10



32A yellow 115V male plug - Sold per 1 or 5

32A yellow 115V male plug - Sold per 1 or 5



Adaptator R54 16A/13A adaptator unit. Sold per 1 or 3

Adaptator R54 16A/13A adaptator unit. Sold per 1 or 3



ADAPTATOR R55 16A/13A adaptator economy. Sold per 1 or 3

ADAPTATOR R55 16A/13A adaptator economy. Sold per 1 or 3



ADAPTATOR R56 16A/13A double adaptator. Sold per 1 or 3

ADAPTATOR R56 16A/13A double adaptator. Sold per 1 or 3

KOHLER®

SDMO®

4/1/2024

HX 6000 TB UK C5 - PORTABLE POWER - GENERATING SET INTENS

This document is not contractual - The SDMO company reserves the right to modify any of the characteristics stated in this document without notice, in a constant effort to improve the quality of its products. *ISO 8528.

SDMO Industries - 270 rue de Kerervem - CS 40047 - 29801 Brest cedex 9 – France - Tél. +33 (0)2 98 41 41 41 - www.kohlersdmo.com



RH1 - Protective cover for HX

4000 – 6000 – 7500T / HXC

4000 – 6000 – 7500T /

PERFORM 4500 – 4500 XL –

5500T – 5500 T XL – 6500 –

6500 XL – 7500 T – 7500 XL /

TECHNIC 6500 – 7500 TE /

DIESEL / TRASH ;

Dimensions : 82 x 58 x 50 cm

Protective cover for HX(C) 4000 – 6000 - 7500T / PERFORM 4500 - 4500
XL - 5500T - 5500 T XL - 6500 - 6500 XL - 7500 T - 7500 XL / TECHNIC
6500 - 7500 TE / DIESEL / TRASH ; Dimensions : 82 x 58 x 50 cm