



HX 7500 T C5

PORTABLE POWER

GENERATING SET Range INTENS

PRODUCT ADVANTAGES

- Solid and high-performance equipment
- Generating set guaranteed 3 years
- HONDA Professional Engine

STAGE V (2016/1628 EU) : This product is compliant with regulation for implementing requirements relating to gaseous and pollutant emission limits in Europe

Range INTENS

Equipment that is robust, long-lasting and simple to use for repetitive operations in difficult conditions.



This product meets the Qualigen charter, which aims to ensure a high level of quality and guarantee the safety of users. Qualigen commitment to safety and quality.

HX 7500 T C5

GENERAL SPECIFICATIONS

Range	INTENS
Frequency (Hz)	50 Hz
Max power (kW) *	5.70
Max power (kVA)	7.10
Nominal voltage (V)	400
Number of Phase	Three phase
Fuel	Petrol
Tank (L)	6.10
75% cons. (l/h) *	2.50
75% Autonomy (h) *	2.40
Sound power level guaranteed LwA dB(A)	97
Acoustic pressure level @1m in dB(A)	83
Acoustic pressure level @7m in dB(A)	69

ENGINE SPECIFICATIONS

Engine brand	HONDA
Engine ref.	GX390_C5
Engine Type	O.H.V.
Start	Starter
Oil shutdown	Oui
Displacement (cm3)	389
Oil system capacity including filters (l)	1.10

ALTERNATOR SPECIFICATIONS

Technology	Collar and brush
AVR Regulation	No
Indication of protection	IP 23
Insulation class	H

PLUGS AND PANEL DESCRIPTIVE

1 230V 10/16A socket - circuit breaker + 1 400V 16A socket - circuit breaker

DIMENSIONS AND WEIGHT

Length (cm)	77
Width (cm)	57
Height (cm)	59
Dry Weight (kg)	80

PACKAGING

Packaging type	Box
Length (cm)	78.50
Width (cm)	58
Height (cm)	59.50
Weight (kg)	82.50
Pallet type	120/80
Number of box by pallet	6
Pallet height (cm)	192
weight of the packaged Pallet (kg)	505

KOHLER®

SDMO®

HX 7500 T C5

ACCESSORIES SUPPLIED




Funnel



User and maintenance manual

OPTIONS



This set includes the hour meter and the differential circuit breaker This set includes the hour meter and the differential circuit breaker.



VERSO 10 T 40A - Manual source inverter for connecting a three-phase generator to a house Manual source inverter for connecting a three-phase generator to a house



RKB2 - Trolley kit for HX 4000 - 6000 - 7500T / HXC 4000 - 6000 - 7500T / TECHNIC 10000 -15000 / VX 200/4 -220-7,5 / WELDARC 300 / TRASH ; Puncture-proof wheels Ø 290 mm Trolley kit for HX 4000 - 6000 - 7500T / HXC 4000 - 6000 - 7500T / TECHNIC 10000 -15000 / VX 200/4 -220-7,5 / WELDARC 300 / TRASH ; Puncture-proof wheels Ø 290 mm



R19 - Maintenance kit for HX 6000 - 7500 T / VX 200/4 including oil, spark plug and air filter Maintenance kit for HX 6000 - 7500 T / VX 200/4 including oil, spark plug and air filter



RH1 - Protective cover for HX 4000 - 6000 - 7500T / HXC 4000 - 6000 - 7500T / PERFORM 4500 - 4500 XL - 5500T - 5500 T XL - 4500 XL - 5500T - 5500 T XL - 6500 - 6500 XL - 7500 T - 7500 XL 6500 - 6500 XL - 7500 T - / TECHNIC 6500 - 7500 TE / DIESEL / TRASH ; Dimensions : 82 x 7500 XL / TECHNIC 6500 - 7500 TE / DIESEL / TRASH ; Dimensions : 82 x 58 x 50 cm Protective cover for HX(C) 4000 - 6000 - 7500T / PERFORM 4500 XL - 5500T - 5500 T XL - 4500 XL - 5500T - 5500 T XL - 6500 - 6500 XL - 7500 T - 7500 XL 6500 - 6500 XL - 7500 T - / TECHNIC 6500 - 7500 TE / DIESEL / TRASH ; Dimensions : 82 x 58 x 50 cm



RPM - Plug kit for all models: 2 x 16A /230V sockets, 1 x CEE17 16A/230V socket, 1 x 32A/230V socket, 1 x 16A/400V socket Plug kit for all models: 2 x 16A /230V sockets, 1 x CEE17 16A/230V socket, 1 x 32A/230V socket, 1 x 16A/400V socket

KOHLER® SDMO®

4/1/2024

HX 7500 T C5 - PORTABLE POWER - GENERATING SET INTENS

This document is not contractual - The SDMO company reserves the right to modify any of the characteristics stated in this document without notice, in a constant effort to improve the quality of its products. *ISO 8528.

SDMO Industries - 270 rue de Kerervern - CS 40047 - 29801 Brest cedex 9 - France - Tél. +33 (0)2 98 41 41 41 - www.kohlersdmo.com