

## PORTABLE INVERTER GENERATOR



# POWERING YOUR life.

Propane: 3000

Propane: 2520

N RUN TIME 34hrs\*

• NOISE LEVEL 58dBA



# **SUPER LIGHTWEIGHT**

Weighs LESS THAN 22kg



## **CLEAN ELECTRICITY**

Power SENSITIVE ELECTRONICS



### ULTRA OUIET

Low noise - HIGH PERFORMANCE



#### **COLD START**

Easy starts in **COLD WEATHER** 



#### PARALLEL READY

Link 2 units for **DOUBLE POWER** 

Sockets



12V DC Automotive



240V 16A Blue UK plug




2 x 240V 13A 16A-13A Adapter



Sockets

Para Link



#### Q Specifications

**START TYPE** Recoil **VOLTAGE (V)** 240 (UK) **ENGINE SIZE (cc)** 149 **FUEL TYPE** Petrol or Propane

**PETROL CAPACITY (L)** 4.5 **OIL TYPE** 10W-30 **OIL CAPACITY (L)** 0.58

**LOW OIL SHUT-OFF** Yes

**CERTIFICATION** UKCA, RoHs, EU V 93001i-DF









16A - 13A 240v Adapter



**LPG Hose** & Adapter



**12V DC Charging Cables** 



**USB** Adapter



Funnel

Champion's 3000 watt dual fuel inverter generator is one of the lightest in the industry at only 21.5kg, making portable power easier than ever. Rely on the 149cc engine with a guiet 58 dBA for up to 11.5 hours of run time on petrol or up to 34 hours\* with propane. The Parallel Kit (sold separately) can increase your output.



### Inside the box

**GENERATOR 12V USB ADAPTER OPERATORS MANUAL LPG HOSE & ADAPTER OIL FUNNEL 16A-13A ADAPTER** 12V DC BATTERY CHARGING CABLE

What you will Need

PETROL OR PROPANE **ENGINE OIL** 

\*Operation at 25% load based on 19kg propane canister. Specifications, descriptions and illustrations are subject to change without notice





