



SHIELD

**CARBON MONOXIDE
AUTO-SHUTOFF**



**AT&M
FUSION**



**Optional
ParaLINK
Parallel Kit**



3000 WATT INVERTER GENERATOR

93001i

93001i-EU

Max AC output:	3000
Noise Level:	58 dBA @ 7m
Running Watts:	2800
Warranty:	3 years
Certification:	CE, UKCA, EU Stage V

i

DESCRIPTION

Champion's 3000 watt inverter generator is one of the lightest in the industry at only 21.5kg, making portable power easier than ever.

Rely on the 149cc engine with a quiet 58 dBA for up to 11.5 hours of run time on petrol (based on 25% load). The Parallel Kit (sold separately) can increase your output.

CO Shield® technology monitors the accumulation of carbon monoxide (CO), a poisonous gas produced by engine exhaust when the generator is running. If CO Shield detects unsafe elevated levels of CO gas, it automatically shuts off the engine.



FEATURES

- 2800 Running Watts
- Super lightweight at only 21.5kg
- CO² Shield for safety
- Ultra quiet at only 58 dBA
- 12v DC Outlet
- True sine wave inverter technology
- Overload protection
- Parallel Connectable with optional ParaLINK kit
- Includes dual port USB adapter.
- Smart Economy Mode



SPECIFICATIONS

Starting Watts	4500
Max Watts	3000
Rated Watts	2800
AC Load	1 x 240v 16 Amp & 2 x 240v 13 Amp adapter (UK) 2 x 220v 16 Amp & 1 x 220v 16 Amp Schuko to Female Adapter (EU)
Frequency	50Hz
Engine	149cc Champion OHV
Fuel Capacity	4.5 Litres
Oil Capacity	0.58 Litres
Noise Level	58 dBA @ 7m
Start Type	Manual
Dimensions (L*W*H)	44 x 29.2 x 45 cm
Certification	CE, UKCA, EU Stage V
Weight (Kg)	21.5
Operation capacity (hr)	11.5 Hrs @ 25% load



INCLUDED

- Oil Funnel
- Dual USB Adapter
- 16A-13A Adapter
- 12v DC battery Charging Cable

